

Deck and Step Lights

Model: **LLED1**



Installation Instructions

1 watt LED

12V DC

3,000K Colour Temperature

IP67

Products:

- LLED1-1L** Single light with 0.5M leads.
- LLED1-KIT6** Six Light Set including a 10 watt Driver.
- LLED1-C1000** 1 Metre accessory extension cable.
- LLED1-C2000** 2 Metre accessory extension cable.
- LLED1-TEE** Tee connector accessory.
- LLED1-IPEC20** Accessory Larger Driver, 20 watt 12V DC.

Installation:

The first step is to sketch your lighting system layout, deciding the location of lights for best results.

Drill 32mm diameter holes for the lights ensuring access for cable connections.

Important notes:

Only use LLED1 Drivers which have the appropriate cable connectors.

The driver supply cord must be plugged into a waterproof socket if in a wet area.

Locate driver in a ventilated location. Do not overload the Driver. Do not cover the Driver. Isolate the Driver while connecting light's to each other. Only turn the power ON once all connections are completed otherwise LED lights may be damaged.

Cables between Driver and lights and between lights should not exceed 3 metres long.

For long length systems use a larger driver to avoid voltage drop issues.

When pushing connectors together, first check the orientation of the Key and Slot to ensure correct alignment of polarity. Then twist cap onto thread to secure and be watertight.

Maintenance:

If LED lights are not rain washed, regular cleaning the 304 Stainless Steel with a soft cloth and soapy water is recommended.

