

**Models: LK1400, LK1500, LK2301,  
LK2302, LK2303, LK1000, LK1200**



## **LED Lighting Fixture Installation Instructions**

### **IMPORTANT:**

- Before commencing installation isolate all cables at that point of installation from the building supply mains.
- Installation by a Registered Electrician is recommended.
- Choose the mounting position carefully taking into account the fixing method, the services behind the wall and the IP rating required for that position.
- **These lighting fixtures have LED modules with components that can be damaged by Electrostatic Discharge. Do not touch the module components as permanent damage can occur.**

Disassemble the lighting fixture by removing the diffuser screws.

Models LK1401 and LK1501 - Detach the LED lamp plate by removing 4 screws.

With the supply cable through the grommet in the base, fix the base to the mounting surface using the 4 holes provided.

To maintain the IP rating ensure that the cable entry is sealed.

Do Not damage the LED module – There are No user serviceable parts.

### **Connect the Supply Cable to the terminal block.**

Connect the Neutral wire to the N Terminal.

Connect the Phase wire to the L Terminal.

- Models LK1401 and LK1501 - Reassemble the LED module onto the Base.
- Reassemble the diffuser onto the base.
- Finally Clip the Colour cover Ring over the base assembly.

---

**!!! Please leave this page with the installation.**

---

**NOTE:** This LED Luminaire does not have a replaceable Lamp or serviceable parts.

### **Do Not Open.**

Consult a Registered Electrician.